

Caterpillar EMCP 4.X



Generac Gateway Side Termination	Description	Wire Color	Customer Side Terminations
TB1 V+	DC+	Red	BTRY +
TB1 V-	DC-	Black	BTRY -
TB1 A	Data +	Orange/White	MB+
TB1 B	Data -	White/Orange	MB -
TB1 GND	Data GND	White/Blue	MB REF
Harness Relay #1	COM	Blue	BTRY -
	N/O	White/Black	REMOTE START

Expected EMCP 4.X Comm Settings:

Baud Rate: 19200

Parity: None

Address: 1

If different settings are required, please contact support.

*If MODEM and signal lights turn off and data is lost after gen crank, this can indicate a brief loss of power. To correct, ensure red and black wires are connected directly to the battery posts.

